

ATG
LED LIGHTING


Carlos Alvarenga | Project Manager

Direct: (909) 296-0209

T: (951) 245-6222

E: carlos.a@atgledlighting.com | W: <https://atgledlighting.com>

10588 Monte Vista Ave, Montclair, CA 91763



ATG ELECTRONICS
SLIM EMERGENCY EXIT SIGN COMBO
ESC02-R1-WH-RC
16.45"W. X 7.24"H. x 2.04"D LED EMERGENCY FIXTURE
LED MODULES WITH FLOOD OPTICS

Horizontal Footcandles
Scale: 1 Inch = 10 Ft.
Light Loss Factor = 1.00
Lumens Per Lamp = N.A. (absolute photometry)
Luminaire Lumens = 173
Mounting Height = 10.00 Ft, Tilt = 60 Degrees
Maximum Calculated Value = 1.06 Fc
Arrangement: Single

PHOTOMETRIC FILENAME : SLIM EMERGENCY EXIT SIGN COMBO ESC02-R1-WH-RC.IES

DESCRIPTIVE INFORMATION (From Photometric File)

ATG ELECTRONICS
SLIM EMERGENCY EXIT SIGN COMBO
ESC02-R1-WH-RC
16.45"W. X 7.24"H. x 2.04"D LED EMERGENCY FIXTURE
LED MODULES WITH FLOOD OPTICS

TEMPLATE SPECIFICATION

Horizontal Footcandles
Scale: 1 Inch = 10 Ft.
Light Loss Factor = 1.00
Lumens Per Lamp = N.A. (absolute photometry)
Luminaire Lumens = 173
Mounting Height = 10.00 Ft, Tilt = 60 Degrees
Maximum Calculated Value = 1.06 Fc
Arrangement: Single

LUMINAIRE LAYOUT INFORMATION

<u>#</u>	<u>X</u>	<u>Y</u>	<u>Z</u>	<u>Orient</u>	<u>Tilt</u>	<u>Roll</u>	<u>Spin</u>	<u>Tilt Correction</u>
1	0.00	0.00	10.00	0.00	60.00	0.00	0.00	1.00